

**HPE Data Collection Daemon (DCD)
Release Notes
VMware ESXi
Version: 3.0.7.0**



Hewlett Packard
Enterprise

Legal Notices

Copyright (C) 2018-2020 Hewlett-Packard Enterprise Development LP

The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Links to third-party websites take you outside the Hewlett Packard Enterprise website. Hewlett Packard Enterprise has no control over and is not responsible for information outside the Hewlett Packard Enterprise Website.

Confidential computer software. Valid license from Hewlett Packard Enterprise required for possession, use, or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

About this document

This document provides details of the currently supported features, enhancement, installation, patches, bugs fixed across releases (if any), known problems, issues, their workarounds, policy details, and documentation details for Data Collection Daemon (DCD) on VMWare ESXi.

Revision History

The following table lists all the details about this document and its release history.

Date	Document details
6 th June 2018	Initial release of DCD for VMware ESXi.
1 st October 2018	Updated for 1.2.5 Release
13 th May 2019	Updated for 2.0.0.0 Release
24 th Sept 2019	Updated for 2.1.0.0 Release
17 th Feb 2020	Updated for 2.3.0.0 Release
9 th Sept 2020	Updated for 3.0.7.0 Release

Table 1: Revision History

Acknowledgments

VMware and VMware ESXi are registered trademarks or trademarks of VMware, Inc. in the United States and/or other jurisdictions. All other third-party trademark(s) is/are property of their respective owner(s).

Open source tools

jsoncpp version 1.8.4: <https://github.com/open-source-parsers/jsoncpp>

Table of Contents

Legal Notices.....	2
About this document.....	3
Revision History.....	3
Acknowledgments	3
Open source tools	3
Introduction.....	5
Features Supported.....	5
Enhancements and Defect Fixes.....	5
Prerequisites.....	6
Supported Hardware and Software	7
Installation / Upgrade.....	7
Known Problems and Workarounds	8
Troubleshooting.....	8
Support Information	9

Introduction

This document discusses the most recent product information on Data Collection Daemon (DCD) which is supported on HPE Superdome Flex and HPE Superdome Flex 280 servers running VMware ESXi host operating system.

Data Collection Daemon (DCD) is an agentless service for HPE Mission Critical Superdome Flex Servers. DCD proactively monitors the health of hardware components that are visible to running operating system instance and reports any errors to management firmware running on Rack Management Controller (RMC) of Superdome Flex. The management service running on RMC processes the data and serves it out of band to client applications.

Features Supported

This version of DCD includes the following major features on VMware ESXi:

- DCD collects inventory data for below listed components:
 - ESXi Hypervisor
 - SAS/SATA Controller - MegaRAID 9361-4i Controller
 - Physical Drives - Superdome Base Chassis Drives (Internal Only)
 - RAID volumes (Logical drives) hosted by MegaRAID 9361-4i Controller
 - Ethernet devices – Intel adapters, Broadcom adapters and Mellanox adapters
 - Fibre Channel Devices – Broadcom adapter and Marvell adapter
- DCD proactively monitors the health of the MegaRAID 9361-4i Controller, attached drives, RAID volumes, Ethernet devices and Fibre channel devices and forwards state change events to RMC.
- Logging is supported in DCD to log messages at different logging levels.
- DCD can push the inventory to RMC immediately upon request from RMC.
- A command line utility “dcdCli” is provided to test the DCD Event Infrastructure.

For more details on supported cards and drives, please refer to HPE Superdome Flex and HPE Superdome Flex 280 Documentation. For more details on supported inventory and events, please refer to README which is part of DCD documents in the /opt/hpe/dcd/ folder on product installation.

Enhancements and Defect Fixes

The following changes were introduced in DCD version 3.0.7.0:

- Added support for VMWare ESXi 7.0.
- Added support to inventory and monitor the following Ethernet devices:
 - 1) HPE Ethernet 1Gb 4-port 366T Adapter
 - 2) HPE Ethernet 10Gb 2-port 521T Adapter
- Added support to inventory and monitor the following Fibre channel devices:
 - 1) HPE SN1200E 16Gb 2p FC HBA
 - 2) HPE SN1100Q 16Gb 2p FC HBA
 - 3) HPE SN1610E 32Gb 2p FC HBA
 - 4) HPE SN1610Q 32Gb 2p FC HBA
- Added support for HPE Superdome Flex 280 servers. DCD now reports physical location information for the following types of devices on these servers:
 - Embedded I/O devices

HPE Data Collection Daemon for VMware ESXi - Release Notes

- PCIe add-on I/O cards
- Resolved QXCR1001742867: DCD_OS_LAST_SHUTDOWN_CRITICAL event is logged even for normal reboots.
- Resolved QXCR1001714728: “show chassis info” reports missing disks as available in FRU inventory for MegaRAID 9361-4i controller.
- Corrected DCD behavior to generate DCD_VOLUME_ERROR event when a non-redundant physical drive of a degraded RAID 1 / RAID 5 / RAID 6 volume (hosted by LSI MegaRAID 9361-4i) fails or goes offline.
- Fixed the issue of TotalFreeSystemMemoryGiB and TotalSystemMemoryGiB attributes being populated as 0 (zero) in system inventory data on certain systems due to esxtop command being denied memory for execution.

The following changes were introduced in DCD version 2.3-0:

- Updated part number table for new SSD models.

The following changes were introduced in DCD version 2.1.0.0:

- Added PartNumber field for LSI MegaRAID 9361-4i in DCD Inventory JSON.
- Modified PartNumber field in DCD Inventory JSON for physical disk drives controllers to use the Spare Part Number.
- Updated part number information reported for specific models of HPE Ethernet adapters.
- Fixed the issue of DCD IPv4Addresses field not being Redfish-compliant when no IPv4 address is configured on the managed server.
- Fixed issue of RAID10 logical volume (configured on LSI MegaRAID 9361-4i) incorrectly showing volume type as “RAID01” in the inventory string.
- Fixed the issue of physical location field for Ethernet device, Drives and Storage Controller being displayed as FFFFFFFFFFFFFFFFFF in inventory and events.
- Integrated with newer version of storelib libstorelib.so.07.1203.0100.0000.

The following changes were introduced in DCD version 2.0.0.0:

- Added support to inventory and monitor Ethernet devices.
- Added support for VMWare ESXi 6.7.

The following changes were introduced in DCD version 1.2.5:

- Added support for two or more MegaRAID 9361-4i controllers per partition.
- Integrated with newer version of storelib libstorelib.so.07.0309.0100.0800.
- Fixed issue of DCD events not being generated if the inventory-refresh happens at a time when a stream of events from MegaRAID 9361-4i are being processed by DCD.
- Fixed issue of missing inventory on a partition where it takes DCD a long time (several minutes or more) to inventory the partition’s hardware configuration.

Prerequisites

- DCD for VMware ESXi 7.0 and VMware ESXi 7.0 U1 needs following version of QLogic Driver, to get the QLogic Fibre channel device inventory and events.
 - QLogic driver version: qlnativefc-4.1.9.0-1OEM.700.1.0.15525992

The QLogic driver can be downloaded from the following location:

ftp://dcdbits:ST1bV%7DSF@ftp.ext.hpe.com/DCD_CH_SEPTEMBER_2020/DCD_VMware_3.0.7.0

- For VMware ESXi 6.5 and 6.7, DCD needs following version of LSI MegaRAID Driver, to get the MegaRAID inventory and events.
 - VMware ESXi 6.5 LSI MegaRAID driver version: 7.709.10.00-1OEM.650.0.0.4598673
 - VMware ESXi 6.7 LSI MegaRAID driver version: 7.709.10.00-1OEM.670.0.0.8169922

LSI MegaRAID driver can be downloaded from the following location:

<https://www.vmware.com/resources/compatibility/detail.php?deviceCategory=io&productid=43866>

Note: These driver resolves a LSI MegaRAID thread hang issue, which caused DCD to stop sending inventory and events to RMC.

Supported Hardware and Software

DCD runs on all hardware models of HPE Superdome Flex Systems.

Supported Firmware:

- On HPE Superdome Flex 280, DCD requires firmware version 1.0.x.
- On HPE Superdome Flex, DCD requires firmware version 2.5.x or later.
- To enable all features introduced in this version of DCD, it is required to upgrade to HPE Superdome Flex firmware version 3.x.

Supported Operating Systems:

DCD version 3.0.7.0 is supported on HPE Superdome Flex server with the following Operating Systems:

- VMware ESXi 7.0 U1
- VMware ESXi 7.0

DCD version 2.3 or earlier is supported on HPE Superdome Flex server with the following Operating Systems:

- VMware ESXi 6.5
- VMware ESXi 6.7

Installation / Upgrade

Download the DCD component for VMware ESXi 7.0 from the following location:

ftp://dcdbits:ST1bV%7DSF@ftp.ext.hpe.com/DCD_CH_SEPTMBER_2020/DCD_VMware_3.0.7.0

Download the DCD offline bundle for VMware ESXi 6.5 and 6.7 from the following location:

<http://vibsdepot.hpe.com/superdome/sdflex/dcd/>

DCD can be installed/updated from the above location using the following command:

```
# esxcli software component apply -d <absolute-path-to-DCD-offline-bundle>
```

To verify if DCD is installed please follow below commands on all VMware ESXi distributions:

HPE Data Collection Daemon for VMware ESXi - Release Notes

- You can use “`esxcli software vib list | grep -i dcd`” to verify if DCD is installed.

For VMware ESXi 7.0 use following commands to check the status of DCD:

- To check the list of files delivered by DCD, you can use the following command:

```
# ls -l /opt/hpedcd
```

- DCD service details and status can be checked using the following command:

```
# /etc/init.d/hpedcd status
```

- DCD service can be started and stopped using the following commands:

```
# To start the service: /etc/init.d/hpedcd start
```

```
# To stop the service: /etc/init.d/hpedcd stop
```

For VMware ESXi 6.5 and ESXi 6.7, DCD service details and status can be checked using the following command:

```
# /opt/hpe/dcd/scripts/dcd_service.sh status
```

Known Problems and Workarounds

- 1) In DCD inventory and events for RAID volumes, the “DeviceName” parameter is an empty value. This is a known behavior.
- 2) DCD will not process logical volume deletion if they are deleted using “storcli delete all” command.
- 3) For MegaRAID 9361-4i controller, DCD may not report RAID volume consistency check events correctly to RMC. This issue will be fixed in a future release.
- 4) For Emulex FC cards, DCD may not generate the correct Physical Location if Emulex FC driver is not upgraded to latest version.
- 5) On VMware ESXi 7.0 only, upon DCD un-installation the files present under “/opt/hpedcd/vital” directory will not be removed even after a reboot.

Troubleshooting

- If DCD service does not start after successful installation, please check the syslog (`/var/log/syslog.log`) for any indication of failures. Use the following command to check if the DCD daemon process is running:

```
ps -TCcjstv | egrep -w "(WID|dcdExecutive)"
```

- The “dcdCli” command line utility enables customers to trigger test event from DCD. Test event help validate DCD’s ability to monitor and generate events for supported hardware. The DCD test event feature can be used as follows:

```
dcdCli [-h][-t <Event-ID> | --test-event <Event-ID>]
```

Example of sending DCD test event:

```
[root@ch-080:/opt/hpedcd/bin] dcdCli -t 708
```

```
dcdCli: Test Event sent to RMC. Please check logs for details.
```

HPE Data Collection Daemon for VMware ESXi - Release Notes

[root@ch-080:/opt/hpedcd/bin]

- For further details about troubleshooting DCD please refer to README.

Support Information

You can report defects related to Data Collection Daemon (DCD) by contacting your local Hewlett Packard Enterprise representative.